




Schedule 80 Fittings

TEE

(continued)


Socket x Socket x Socket



Part Number	Size	G	G1	H	H1	L	M	Approx. Wt. (Lbs.)
801-050	5	3-1/8	3-1/8	5-25/32	5-25/32	11-5/8	6-13/32	6.03
801-050F	5	5-1/2	5-1/2	8-1/2	8-1/2	17	6-5/16	13.26
801-060	6	3-25/32	3-25/32	6-25/32	6-25/32	13-19/32	7-19/32	9.52
801-080	8	4-13/16	4-13/16	8-7/8	8-7/8	17-3/4	9-23/32	21.21
801-080F	8	7-5/8	7-5/8	11-7/8	11-7/8	23-3/4	9-5/8	22.84
801-100	10	5-3/4	5-3/4	10-13/16	10-13/16	21-5/8	11-19/32	37.89
801-100F	10	9	9	14-1/4	14-1/4	28-1/2	11-15/16	39.82
801-120	12	6-15/16	6-15/16	12-15/16	12-15/16	25-7/8	14-1/4	54.45
801-120F	12	11-1/4	11-1/4	17-1/2	17-1/2	35	14-1/8	67.13
801-140	14	7-1/32	7-1/32	14-7/32	14-1/32	28-7/16	15-21/32	63.61
801-140F	14	12-1/4	12-1/4	19-1/4	19-1/4	38-1/2	15-1/2	103.37
801-160F	16	13	13	21	21	42	17-11/16	144.87
801-180F	18	13-3/4	13-3/4	22-3/4	22-3/4	45-1/2	19-7/8	182.75
801-200F	20	16-3/8	16-3/8	26-3/8	26-3/8	52-3/4	22-1/16	284.24
801-240F	24	20-1/4	20-1/4	32-1/4	32-1/4	64-1/2	26-7/16	335.00

REDUCING TEE

Socket x Socket x Socket



Part Number	Size	G	G1	G2	H	H1	H2	L	M	M1	Approx. Wt. (Lbs.)
801-101	3/4x3/4x1/2	19/32	23/32	19/32	1-19/32	1-19/32	1-19/32	3-3/16	1-13/32	1-3/16	.14
801-130	1x1x1/2	19/32	7/8	19/32	1-23/32	1-3/4	1-23/32	3-7/16	1-3/4	1-3/16	.20
801-131	1x1x3/4	11/16	27/32	11/16	1-27/32	1-27/32	1-27/32	3-21/32	1-3/4	1-13/32	.23
801-157	1-1/4x1x3/4	11/16	1-1/16	5/8	1-15/16	2-1/16	1-7/8	3-13/16	2-1/8	1-7/16	.30
801-158	1-1/4x1x1	13/32	15/16	13/32	2-1/8	1-31/32	1-15/16	4	2-1/16	1-11/16	.33
801-159	1-1/4x1x1-1/4	15/16	1-1/32	7/8	2-3/16	2-5/32	2-1/8	4-5/16	2-1/16	2-1/16	.39
801-166 ¹	1-1/4x1-1/4x1/2	7/8	1-13/32	7/8	2-3/32	2-3/8	2-3/32	4-7/32	2-1/8	1-3/4	.42
801-167	1-1/4x1-1/4x3/4	5/8	31/32	5/8	1-15/16	1-31/32	1-15/16	3-7/8	2-1/8	1-13/32	.28
801-168	1-1/4x1-1/4x1	27/32	1-1/32	27/32	2-3/32	2-5/32	2-3/32	4-7/32	2-3/32	1-3/4	.34

¹ Outlet sized with bushing