


**COUPLING**

(continued)


Socket x Socket



Part Number	Size	L	M	N	Approx. Wt. (Lbs.)
829-140	14	14-7/16	15-5/8	3/8	29.70
829-140F	14	16-1/4	15-1/2	2-1/4	29.70
829-160F	16	19-1/2	17-11/16	3-1/2	42.38
829-180F	18	22	19-7/8	4	63.81
829-200F	20	23-3/4	22-1/16	3-3/4	86.58
829-240F	24	29-1/4	26-7/16	5-1/4	147.22

REDUCER COUPLING

Socket x Socket



Part Number	Size	L	M	M1	N	Approx. Wt. (Lbs.)
829-101	3/4x1/2	2-3/32	1-13/32	1-5/32	7/32	.07
829-130	1x1/2	2-3/16	1-23/32	1-13/32	7/32	.11
829-131	1x3/4	2-13/32	1-23/32	1-13/32	1/4	.10
829-166	1-1/4x1/2	2-9/16	2-3/32	1-5/32	7/16	.13
829-167	1-1/4x3/4	2-19/32	2-3/32	1-5/8	11/32	.17
829-168	1-1/4x1	2-11/16	2-1/8	1-3/4	5/16	.17
829-209	1-1/2x1/2	2-27/32	2-11/32	1-3/16	19/32	.19
829-210	1-1/2x3/4	2-7/8	2-3/8	1-13/32	17/32	.21
829-211	1-1/2x1	2-7/8	2-11/32	1-15/16	3/8	.26
829-212	1-1/2x1-1/4	2-13/16	2-13/32	2-1/8	5/32	.22
829-247	2x1/2	3-3/32	2-7/8	1-5/32	11/16	.30
829-248	2x3/4	3-7/32	2-7/8	1-13/32	23/32	.30
829-249	2x1	3-1/8	2-7/8	1-23/32	17/32	.33
829-250	2x1-1/4	3-11/32	2-7/8	2-3/32	19/32	.31
829-251	2x1-1/2	3-7/32	2-27/32	2-11/32	1/4	.30
829-290 ¹	2-1/2x1-1/4	3-29/32	3-1/2	2-3/8	15/16	.57
829-291	2-1/2x1-1/2	3-3/4	3-1/2	2-3/8	19/32	.51
829-292	2-1/2x2	3-21/32	3-15/32	2-27/32	13/32	.48
829-335	3x1	4-7/16	4-1/8	2-7/8	1-7/16	1.00
829-336 ¹	3x1-1/4	4-7/32	4-5/32	2-29/32	1-1/16	.94
829-337	3x1-1/2	3-1/2	4-3/16	2-3/8	7/32	.71

¹Outlet sized with bushing