




Schedule 80 Fittings

TEE


Socket x Socket x Fipt



Part Number	Size	G	G1	H	H1	L	M	Approx. Wt. (Lbs.)
802-002	1/4	5/16	3/8	15/16	15/16	1-29/32	7/8	.05
802-005	1/2	19/32	21/32	1-15/32	1-11/32	2-15/16	1-3/16	.14
802-007	3/4	5/8	5/8	1-19/32	1-13/32	3-3/16	1-13/32	.14
802-010	1	11/16	3/4	1-13/16	1-5/8	3-13/16	1-13/16	.23
802-012	1-1/4	13/16	1-1/16	2-3/32	1-15/16	4-5/32	2-3/32	.34
802-015	1-1/2	29/32	1-1/4	2-11/32	2-5/32	4-11/16	2-3/8	.49
802-020	2	1-9/32	1-15/32	2-13/16	2-13/32	5-21/32	2-7/8	.77
802-030	3	1-31/32	2-1/8	3-3/4	3-17/32	7-15/32	4-5/16	2.31
802-040	4	2-11/32	2-21/32	4-5/8	4-5/32	9-7/32	5-9/32	3.37
802-060F	6	3-3/4	8-5/8	6-3/4	10-1/8	13-11/2	7-5/8	14.19
802-080F	8	4-13/16	10-13/16	8-13/16	12-9/16	17-11/16	9-11/16	25.92

REDUCING TEE

Socket x Socket x Fipt



Part Number	Size	G	G1	H	H1	L	M	M1	Approx. Wt. (Lbs.)
802-101	3/4x3/4x1/2	19/32	25/32	1-19/32	1-7/16	3-7/32	1-13/32	1-3/16	.14
802-130	1x1x1/2	7/16	29/32	1-9/16	1-5/8	3-1/8	1-23/32	1-7/16	.18
802-131	1x1x3/4	21/32	13/16	1-13/16	1-17/32	3-5/8	1-23/32	1-3/8	.21
802-166	1-1/4x1-1/4x1/2	7/16	1-1/8	1-11/16	1-27/32	3-3/8	2-3/32	1-3/16	.26
802-167 ¹	1-1/4x1-1/4x3/4	7/8	1-23/32	2-1/8	2-7/16	4-7/32	2-3/32	1-3/4	.40
802-168	1-1/4x1-1/4x1	27/32	1-1/32	2-3/32	1-29/32	4-7/32	2-3/32	1-11/16	.33
802-209 ¹	1-1/2x1-1/2x1/2	11/16	1-9/16	2-3/32	2-9/32	4-5/32	2-11/32	1-13/32	.40
802-210 ¹	1-1/2x1-1/2x3/4	7/8	1-27/32	2-1/4	2-19/32	4-1/2	2-3/8	1-11/16	.51
802-211	1-1/2x1-1/2x1	27/32	1-9/32	2-1/4	2-3/32	4-15/32	2-3/8	1-11/16	.41
802-212	1-1/2x1-1/2x1-1/4	1-1/32	1-5/32	2-7/16	2-3/32	4-27/32	2-3/8	2-1/16	.47
802-247 ¹	2x2x1/2	1/2	1-1/2	2	2-7/32	4	2-7/8	1-3/16	.45
802-248	2x2x3/4	5/8	1-3/8	2-1/8	2-3/32	4-1/4	2-7/8	1-3/8	.47

¹ Outlet sized with bushing